

T3 Prox Keypad Programming – Cheat Sheet

Factory Code = 123456

1. **Enter Program Mode** (wait for Green light, before pressing AL button)

1 2 3 4 5 6	A _L
-------------	----------------

All programming functions are performed while the lock is in program mode.

2. **Change Factory Code to New Master Code (Must be 6 digits)**

A _L	1	A _L		A _L		*
----------------	---	----------------	--	----------------	--	---

(Enter Master Code) (Re Enter Master Code)

3. **Enter Date**

A _L	38	A _L		*
----------------	----	----------------	--	---

(Enter Month Day Year- Use MMDDYY)

4. **Enter Time**

A _L	39	A _L		*
----------------	----	----------------	--	---

(Enter Military Time)

5. **Enter Day of Week**

A _L	40	A _L		*
----------------	----	----------------	--	---

(Enter 1 – 7, 1 = Sun, 7 = Sat)

6. **Add New Users: Prox Card Only**

A _L	2	A _L		*	Present Card
A _L	2	A _L		*	Present Card

(User ID #)

7. **Add New Users: Pin Only**

A _L	2	A _L		A _L		*
A _L	2	A _L		A _L		*

(User ID #) (Enter User code 3–6 digits)

8. **Add New Users requiring Prox Card & Pin Number** (Use Steps 6 & 7 for each user requiring Prox & Pin)

A _L	2	A _L		A _L		*
A _L	2	A _L		*	Present Card	

9. **User Enable with Timeout**

A _L	5	A _L		A _L		*
----------------	---	----------------	--	----------------	--	---

(User ID #) (Enter 1 – 999 hours)

10. **Passage Mode**

A _L	45	*
----------------	----	---

11. **Re-lock Mode**

A _L	46	*
----------------	----	---

12. **Timed Passage Mode**

A _L	47		*
----------------	----	--	---

(Enter 1 – 999 hours)

13. **Print Audit Trail IR1**

A _L	55	*
----------------	----	---